

# GOODWE

## Lynx A Series

### 5kWh | Low Voltage Battery

Harnessing the reliability of lithium iron phosphate (LFP) battery cell technology to ensure safety and longevity, GoodWe's low-voltage Lynx A Series has been designed to cater to residential requirements. With a focus on maximizing self-consumption and providing reliable solar power backup, this system ensures a seamless energy experience for homeowners. Moreover, the battery presents high energy density, enabling effective storage of significant energy within a confined space.



#### Smart Control

- Remote diagnosis & update via inverter
- Auto reboot after undervoltage



#### Friendly & Thoughtful Design

- Compact and lightweight design
- Cell-to-pack (CTP) battery design



#### Superb Safety & Reliability

- Reliable LFP technology with high cycle stability
- Insulation resistance test



#### Flexible & Adaptable Applications

- Possess scalability to meet demand
- Compatible with GoodWe residential storage inverters

Technical Data		LX A5.0-10
Usable Energy (kWh) <sup>*1</sup>		5
Battery Module		LX A5.0-10: 51.2V 5.0kWh
Number of Modules		1
Cell Type		LFP (LiFePO4)
Nominal Voltage (V)		51.2
Operating Voltage Range (V)		47.5 ~ 57.6
Nominal Dis- / Charge Current (A) <sup>*2</sup>		60
Nominal Power (kW) <sup>*2</sup>		3
Operating Ambient Temperature Range (°C)		Charge: 0 ~ +50; Discharge: -10 ~ +50
Relative Humidity		0 ~ 95%
Max. Operating Altitude (m)		3000
Communication		CAN
Weight (kg)		40
Dimensions (W x H x D mm)		442 x 133 x 420 (Excluding hanger); 483 x 133 x 452 (Including hanger)
Ingress Protection Rating		IP21
Mounting Method		Cabinet / Floor stacked / Wall-Mounted
Standard and Certification	Safety	IEC62619, IEC63056, IEC62040-1
	EMC	EN IEC61000-6-1, EN IEC61000-6-2, EN IEC61000-6-3, EN IEC61000-6-4
	Transportation	UN38.3, ADR

\*1: Test conditions, 100% DOD, 0.2C charge & discharge at +25 ±2°C for battery system at beginning life. System Usable Energy may vary with different Inverter.

\*2: Nominal Dis- / Charge Current and power derating will occur related to Temperature and SOC.


\*3: Based on Using Battery Combiner Box to parallelize battery modules.

n: Max 15.


\*: Please visit GoodWe website for the latest certificates.

\*: All pictures shown are for reference only. Actual appearance may vary.

## Installation Method (Excluding Hanger)




Method 1: Floor-mounted



Method 2: Cabinet

## Installation Method (Including Hanger)



Method 3: Wall-mounted